

PGM-8

PASSIVE STEREO MIXER



Overview

The Yorkville PGM8 delivers all of the essential features needed in a professional mixer in a convenient, ultra-compact package.

High quality 60mm faders throughout, effective fully featured input channel design, 24-bit digital effects, and break switch make the PGM8 the perfect mixer for live music applications and for small installs.

Features

- Four Mono Input Channels with XLR & 1/4-inch TRS inputs
- Channel 4 Mono Input has a Hi-Z input switch
- Two Additional stereo line input channels (5/6 and 7/8)
- Additional XLR mono input per stereo channel
- Input gain level control with Non-defeatable soft multi-slope compressor on every input
- 3-band EQ, High Pass Filter, Monitor send, Effect Send, Clip LED, Mute Switch and Pan control per Channel
- Global 48 volt Phantom Power
- 7-band stereo graphic EQ on Main Outs
- BREAK Switch (mutes all input channels)
- Sixteen 24-bit digital audio effects
- Headphone Level Control

Specifications

System Type	Mixer
Powered or Passive	Passive
Number of Channels	8
Mono Channel EQ	3-band
Main Out EQ	7-band
Balance Controls	Yes
Pan Controls	Yes
Channel Overload Protection	Yes
Inputs - XLR (bal)	6
Inputs - 1/4"	6
Inputs - RCA (unbal)	1 stereo pair
Phantom Power	48 volt + LED indicator
VU Meter	2 x 10 Segment LEDs
Headphone Monitor Features	Yes
Internal Effects	24 bit stereo 16 effects
Effects Send	2 (1 internal, 1 external)
Effects Return to Main	Yes
Effects Return to Monitor	Yes
Reverb / Effects Footswitch	Yes
Record Outputs	1 stereo pair
Mixer - Freq Resp (Tone and EQ Flat, +/-2dB)	20Hz - 20KHz
Power Consumption (typ/max)	26VA (typical)
Chassis Construction	Steel
Dimensions (DWH, inches)	14.2 x 12.8 x 2.8
Dimensions (DWH, cm)	36 x 32.5 x 7
Weight (lbs/kg)	8.5/3.8
Box Dimensions (LxWxH, inches)	16 x 17.3 x 5.5
Box Dimensions (LxWxH, cm)	40 x 44 x 14

Specifications subject to change without notice

