

MM5D

POWERED MIXER



Overview

The MicroMix MM5D powered box mixer is the ideal PA solution for most applications where 2 x 90 watts (stereo) is enough power yet input flexibility is required.

Balanced XLR mic, 1/4-inch phone and dual RCA line inputs, onboard user controlled digital effect unit and tape outs (with separate level controls) make the MM5D the perfect powered mixer for live PA, rehearsal, installation or announcement PA applications.

Features

- 5 input channels
- 2-band EQ, level & effects send control per channel
- Additional CD/Tape in with level control
- Separate Record out with level control
- Stereo 7-band master Graphic EQ
- 2 x 90w powered out (stereo)
- 1/4-inch & Speakon speaker output jacks
- On-board Digital effects

Specifications

System Type	Mixer
Powered or Passive	Powered
Power Output @ 8 Ohms	2 x 60 Watts
Power Output @ 4 Ohms	2 x 90 Watts
Number of Channels	5
Channel Effects	Yes
Internal Effects	16 Digital Effects
Mono Channel EQ	2-band shelving
Main Out EQ	7-band
Effects Send	No
Effects Return	No
Effects Return to Main	Yes
Effects Return to Monitor	No
Inputs - XLR (bal)	5 (Ch.1 - 5)
Inputs - 1/4"	5 (Ch.1 - 5)
Inputs - RCA (unbal)	1 stereo pair
Outputs - 1/4"	2
Outputs - Speakon 4-pin	2
Record Outputs	Stereo RCA with level control
Other Features	Hi-Z Input (Ch.5)
Clip LED	All Channels / EFX / Main
Mixer - Freq Resp (Tone and EQ Flat, +/-2dB)	40Hz - 20KHz
Power Consumption (typ/max)	1.0 A @ 120VAC 0.5 A @ 230VAC
Protection	Clip limiter, thermal shutdown
Cooling	Passive & Internal Fan
Dimensions (DWH, inches)	9 x 17.75 x 6
Dimensions (DWH, cm)	22.85 x 45 x 15.25
Weight (lbs/kg)	19.2 / 9.7
Box Dimensions (LxWxH, inches)	20.5 x 13.4 x 8.3
Box Dimensions (LxWxH, cm)	52 x 34 x 21

Specifications subject to change without notice

